



KVASER MEMORATOR LIGHT HS

EAN 73-30130-00513-6

Designed for troubleshooting any CAN-based (controller area network) system, the Kvaser Memorator Light HS is an easy-to-use tool for logging serial data, with no preconfiguration or software setup required. With an autobaud function that determines CAN bus bit rate, the Kvaser Memorator Light can be attached to any high-speed CAN bus without configuration. All CAN bus traffic is logged in a circular buffer, overwriting the oldest data when the buffer becomes full. A separate circular buffer keeps track of error frame conditions and the message traffic that occurs near the conditions.

KVASER MEMORATOR LIGHT HS

EAN 73-30130-00513-6

Major Features

- Single high-speed CAN channel (compliant with ISO 11898-2).
- Supports both 11-bit (CAN 2.0A) and 29-bit (CAN 2.0B active) identifiers.
- Supports bit rates from 10 Kbit/sec up to 1 Mbit/sec.
- Auto detects bit rate - removes the need for configuration.
- Always in silent mode - log bus traffic without interfering.
- 1 GByte of internal memory for message storage.
- All received CAN frames recorded in a circular buffer - oldest data overwritten by newest.
- A second circular buffer records 1000 messages before and after an error frame occurs.
- The Kvaser Memorator Light extraction software provides easy access to the recorded data when connected to the device via a USB port. The tool supports multiple formats used by popular analysis software. In addition, the extraction software allows the user to clear and reinitialize the device's memory

Technical Data

| | |
|-----------------------------|--|
| Temp Range | -40 - 85 °C |
| Messages Per Second Receive | 20000 mps |
| Weight | 150 g |
| Length | 90 mm |
| Height | 25 mm |
| Channels | 1 |
| Certificates | CE, RoHS |
| Categories | PC INTERFACES, Dataloggers |
| OS | Linux, Windows 10, 8, 7, Vista, and XP |
| Galvanic Isolation | No |
| Error Frame Generation | No |
| Error Counters Reading | No |
| Silent Mode | Yes |
| Sound | No |

WARRANTY

2-Year Warranty. See our General Conditions and Policies for details.

SUPPORT

Free Technical Support on all products available by contacting support@kvaser.com

SOFTWARE

Documentation, software and drivers can be downloaded for free at: www.kvaser.com/downloads

Kvaser CANlib SDK is a free resource that includes everything you need to develop software for the Kvaser CAN interfaces. Includes full documentation and many program samples, written in C, C++, C#, Delphi, Java, Python, and Visual Basic.

All Kvaser CAN interface boards share a common software API. Programs written for one interface type will run without modifications on the other interface types!

J2534 Application Programming Interface available.

RP1210A Application Programming Interface available.

Online documentation in Windows HTML-Help and Adobe Acrobat format.

